



EW-7711UMn V3.0

150Mbps Wireless 802.11n USB Adapter



EW-7711UMn is a mini size wireless USB adapter which provides a simple and easy way to add or upgrade wireless connectivity to your desktop or notebook computer. This USB adapter supports higher data rate up to 150Mbps and is complies with wireless 802.11n device. You can just plug it into your computer's USB port and enjoy incredible high-speed wireless network access.

Complies with wireless 802.11n devices with data rate up to 150Mbps

EW-7711UMn is complied with wireless 802.11b/g/n standards. Built-in with the latest wireless technology, EW-7711UMn can increase the coverage 3 times more* and reduce "dead spots" within the wireless range. The transmission data rate when connecting with wireless 802.11n devices is up to 150Mbps, which makes signal travel farther and maintain wireless connections much reliable than standard wireless 802.11b/g network.

Supports WPS (Wi-Fi Protected Setup) configuration

Wi-Fi Protected Setup (WPS) is a standard for easy and secure establishment of a wireless network. This wireless USB adapter supports hardware WPS configuration. When both ends of the wireless connection use Edimax wireless solution with WPS, it will automatically configure the wireless network with robust WPA data encryption and authentication.

Supports multi-language Ezmax setup wizard

The included Ezmax setup wizard with 16 languages and friendly UI will walk you through configuring EW-7711UMn to your wireless network.

Portable and compact design

The compact design of EW-7711UMn is convenient to carry for all mobile users.

Includes Hardwire USB cable to improve the performance

The USB adapter achieves the impressive performance when plugging in hardwire USB cable included in the package.

* The EZMax Setup CD Wizard only supports Edimax wireless Series.

FEATURES AND TECHNICAL SPECIFICATIONS

- Complies with wireless 802.11b/g/n standards with data rate up to 150Mbps
- Increases wireless coverage 3 times further
- Includes multi-language EZmax setup wizard.
- Supports 64/128-bit WEP, WPA, WPA2 encryption and WPS

HARDWARE INTERFACE	STANDARD	FREQUENCY BAND
<ul style="list-style-type: none"> USB 1.0/2.0 Type A WPS Button 	<ul style="list-style-type: none"> IEEE802.11b, 802.11g, 802.11n 	<ul style="list-style-type: none"> 2.4000~2.4835GHz (Industrial Scientific Medical Band)
DATA RATES	INSTALLATION	LED
<ul style="list-style-type: none"> 11b: 1/2/5.5/11Mbps 11g: 6/9/12/24/36/48/54Mbps 11n (20MHz): MCS0-7 (up to 72Mbps) 11n (40MHz): MCS0-7 (up to 150Mbps) 	<ul style="list-style-type: none"> Multi-language EZmax Setup Wizard 	<ul style="list-style-type: none"> Link/Activity
SECURITY	DIMENSION	HUMIDITY & TEMPERATURE
<ul style="list-style-type: none"> WEP 64/128, WPA, WPA2 Supports Cisco CCX Hardware WPS configuration 	<ul style="list-style-type: none"> 61(H) x 20.5(W) x 10(D) mm 	<ul style="list-style-type: none"> Max. 95% (Non Condensing) 32~104°F (0~40°C)
SYSTEM REQUIREMENTS	OUTPUT POWER	CERTIFICATIONS
<ul style="list-style-type: none"> Windows 2000/XP/Vista/7, Linux and Mac OS 	<ul style="list-style-type: none"> 11n: 14dBm±1dBm, 11g: 14dBm±1dBm, 11b: 17dBm±1dBm 	<ul style="list-style-type: none"> CE, FCC, WiFi

NETWORK SETUP DIAGRAM AND RELATED PRODUCTS

An example of how the EW-7711UMn can be setup:

- Connects the EW-7711UMn wireless adapter to your computer.
- Setups the wireless connection by running the multi-language EZmax wizard.
- Connects to 802.11b/g/n wireless access point or broadband router.

